

## BILANS MOCY

Lp.			Ilość	Moc	P <sub>i</sub>	k <sub>z</sub>	P <sub>z</sub>	cosφ	tg φ	P <sub>z1</sub>	Q <sub>z1</sub>	S <sub>z1</sub>
				[W]	[W]		[W]			[W]	[Var]	[VA]
Istniejąca szafka oświetleniowa SO1												
	Obwód 1											
	Siteco oprawa 5XA5904F1A08 Streetlight 10 micro LED, 15,9W	szt	5	16	80	1,00	80	0,93	0,40	80	32	86
	Obwód 2											
	Siteco oprawa 5XA5904F1A08 Streetlight 10 micro LED, 15,9W	szt	6	16	96	1,00	96	0,93	0,40	96	38	103
	Projektowana Oprawa 3000lm LED, 21W	szt	5	21	105	1,00	105	0,99	0,14	105	15	106
	Obwód 3											
	Siteco 5XA5131E1A08A4 1xLED 31,4W/740 DL@; 30 LED IP66	szt	1	31	31	1,00	31	0,93	0,40	31	12	34
	Siteco 5XA5131J1A08A5 1xLED 61,7W/740 DL@; 30 LED IP66	szt	3	62	185	1,00	185	0,93	0,40	185	73	199
	Obwód 4											
	5XA5904F1A08 Streetlight 10 micro LED, 15,9W, 1230lm, 3000K	szt	10	16	160	1,00	160	0,93	0,40	160	63	172
	Siteco 5XA5914E1A08 Streetlight 10 mini LED, 27.4W	szt	2	28	56	1,00	56	0,93	0,40	56	22	61
	RAZEM SO1				714		714	0,94	0,37	714	32	761

P<sub>i</sub> - Moc zainstalowanak<sub>z</sub> - Współczynnik jednoczesnościP<sub>z</sub> - Moc zapotrzebowana

cos φ - współczynnik mocy

tg φ - współczynnik mocy

P<sub>z1</sub> - Moc czynna w tablicyQ<sub>z1</sub> - Moc bierna w tablicyS<sub>z1</sub> - Moc pozorna w tablicy